3. Electrical Parts List

Location no	Code no.	Description Specification	Remarks
	AH26-00239A	TRANS POWER-230V/115V,50HZ;-,MAX-J530,-,	OPTION
	AH26-00239B	TRANS POWER-220V/110V,50HZ;-,MAX-J530,-,	OPTION
	AH39-00257A	POWER CORD;CP2,250V,2.5A,1830MM	EUROPE
	AH39-00257D	POWER CORD;CP2,KS,250V,2.5A,1830MM	KOREA
	AH39-00320C	CBF COAXIAL CABLE;MAX-L68,110REC,-,1007#	
	AH40-00050A	TUNER-PACK ASSY;FM/MW,RDS,FM87.5~108.0MHz	EUROPE(RDS)
	AH40-00043A	TUNER-PACK ASSY;FM/MW/LW,RDS,FM87.5~108.0MHz	EUROPE(RDS)
	AH40-00042A	TUNER-PACK ASSY;FM/MW/LW,RDS,FM64~108.0MHz	CIS(RDS)
	AH40-00044A	TUNER-PACK ASSY;FM/MW,MW520~1720KHz	ASIA(T-BAND)
	AH40-00045A	TUNER-PACK ASSY;FM/MW/LW,FM64~108.0MHz	CIS(NO RDS)
	AH40-00046A	TUNER-PACK ASSY;FM/MW/LW,FM87.5~108.0MHz	LW BAND
	AH40-00049A	TUNER-PACK ASSY;FM/MW/SW1/SW2	SW BAND
	AH42-20001P	ANT LOOP;-,KS971120-01,18.5UH##10%,-	
	AH39-00320C	CBF COAXIAL CABLE;MAX-L68,110REC,-,1007#	
	AH59-01159P	REMOCON-ASSY;MAX-J530,SAMSUNG,-,-,28KEY,	EUR
	AH59-01159N	REMOCON-ASSY;MAX-J530,SAMSUNG,-,-,28KEY,	KOR
	AH59-00162A	DECK;CMS300-V	
	AH92-00922A	**ASSY PCB-CD;G3HI-3CD,3.5S**	
WIC401	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D	
WIC402	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D	
X201	2802-000211	RESONATOR-CERAMIC;16.93MHz,0.5%,TP,10.0x	
CW103	3708-001131	CONNECTOR-FPC/FFC/PIC;5P,1.25MM,STRAIGHT	
CW101	3708-001252	CONNECTOR-FPC/FFC/PIC;16P,1MM,STRAIGHT-F	
CW105	3708-001438	CONNECTOR-FPC/FFC/PIC;22P,1.25MM,ANGLE,S	
CW107	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN	
CW104	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRA	
CW106	AH39-00060A	LEAD CONNECTOR ASSY;-,51015-08,51004-08,	
CW102	AH39-20561P	LEAD CONNECTOR ASSY;-,5295,PHR,6P,150mm,	
D301	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T	
ZD301	0403-000344	DIODE-ZENER;UZ3.9B,3.7-4.1V,500MW,DO-35,	
ZD402	0403-000352	DIODE-ZENER;UZ4.7BM,4.4-5V,500MW,DO-35,T	
ZD401	0403-000361	DIODE-ZENER;UZ6.2BSB,5.96-6.27V,500MW,DO	
Q302	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
Q301	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
IC201	0904-001524	IC-DSP;5L9290,-,QFP,48P,472MIL,16.934	
IC301	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE	
IC101	1204-001799	IC-ASP;KB9226,LQFP,48P,393MIL,PLASTIC	
R117	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R810	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R807	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R808	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R302	2001-001006	R-CARBON;82OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R114	2007-000001	R-CHIP;68Kohm,5%,1/8W,TP,2012	
J1	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J10	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J2	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J8	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J9	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J7	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J5	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J4	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J3	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JW21	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	
R501L	2007-000282	R-CHIP;100Kohm,5%,1/8W,TP,2012	
R501R	2007-000282	R-CHIP;100Kohm,5%,1/8W,TP,2012	
R201	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R502L	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R502R	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
MR2	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
MR3	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R132	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R133	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R809	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R108	2007-000308	R-CHIP;10ohm,5%,1/8W,TP,2012	
R124	2007-000338	R-CHIP;120Kohm,5%,1/8W,TP,2012	
R125	2007-000338	R-CHIP;120Kohm,5%,1/8W,TP,2012	
R121	2007-000409	R-CHIP;15Kohm,5%,1/8W,TP,2012	
R110	2007-000409	R-CHIP;15Kohm,5%,1/8W,TP,2012	
R113	2007-000444	R-CHIP;180Kohm,5%,1/8W,TP,2012	
R208	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R207	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R206	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R205	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R204	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R209	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R811	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R806	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R805	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R804A	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R804	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R118	2007-000477	R-CHIP;1Mohm,5%,1/8W,TP,2012	
R204	2007-000477	R-CHIP;1Mohm,5%,1/8W,TP,2012	

Location no	Code no.	Description Specification	Remarks
R116	2007-000546	R-CHIP;20Kohm,5%,1/8W,TP,2012	
R210	2007-000572	R-CHIP;220ohm,5%,1/8W,TP,2012	
R128	2007-000653	R-CHIP;27Kohm,5%,1/8W,TP,2012	
DR2	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
DR1	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R813	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R129	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R123	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R101	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R104	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R103	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R102	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R126	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R120	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R115	2007-001177	R-CHIP;8.2Kohm,5%,1/8W,TP,2012	
R112	2007-001195	R-CHIP;820Kohm,5%,1/8W,TP,2012	
R127	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R119	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R106	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R105	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R107	2007-001216	R-CHIP;82ohm,5%,1/8W,TP,2012	
R301	2008-000140	R-FUSIBLE;2.2ohm,5%,1/2W,AA,TP,3.5x9.4mm	
C113	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
C603A	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
C806A	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
C804	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C805	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C806	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C891	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C131	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C132	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C204	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C205	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C211	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C130	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C115	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C116	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C118	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C124	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C129	2203-000203	C-CER,CHIP;100nF,10%,16V,X7R,TP,2012,2mm	
C402	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C401	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C209	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C207	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C134	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C121	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C105	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C103	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C305	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C304	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C218	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C216	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C214	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C213	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C126	2203-000495	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,2012	
C127	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
C803	2203-000787	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C119	2203-000802	C-CER,CHIP;33nF,10%,50V,X7R,TP,2012	
C128	2203-000802	C-CER,CHIP;33nF,10%,50V,X7R,TP,2012	
C125	2203-000840	C-CER,CHIP;0.39NF,5%,50V,C0G,TP,2012	
C208	2203-000858	C-CER,CHIP;0.039NF,5%,50V,C0G,TP,2012	
C111	2203-000892	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C112	2203-000892	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C124A	2203-001064	C-CER,CHIP;56NF,10%,50V,C0G,TP,2012	
C106	2203-001137	C-CER,CHIP;68nF,+80-20%,50V,Y5V,TP,2012,	
C122	2203-001137	C-CER,CHIP;68nF,+80-20%,50V,Y5V,TP,2012,	
C203	2203-001223	C-CER,CHIP;0.82nF,10%,50V,X7R,TP,2012	
C102	2203-001537	C-CER,CHIP;1nF,10%,50V,X7R,TP,2012	
C117	2203-001537	C-CER,CHIP;1nF,10%,50V,X7R,TP,2012	
C502L	2203-001537	C-CER,CHIP;1nF,10%,50V,X7R,TP,2012	
C502R	2203-001537	C-CER,CHIP;1nF,10%,50V,X7R,TP,2012	
C104	2203-001551	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,2012	
C202	2203-001619	C-CER,CHIP;0.027nF,5%,50V,NP0,TP,2012	
C201	2203-001619	C-CER,CHIP;0.027nF,5%,50V,NP0,TP,2012	
C215	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C217	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C302	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C303	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C212	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C108	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C107	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C101	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C133	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C123	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5	
C301	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5	
C114	2401-001625	C-AL;6.8uF,20%,50V,GP,TP,5x11,5	
C501L	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
C501R	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
C120	2401-001968	C-AL;470nF,20%,50V,GP,TP,5x11mm,5mm	

Location no	Code no.	Description	Specification	Remarks
C135	2401-001968	C-AL;470nF,20%,50V,GP,TP,5x11mm,5mm		
C801	2401-002183	C-AL;220uF,20%,16V,GP,TP,8x9,5mm		
WIC801	AC14-12001G	IC;KA78L05,T,-		
	AH41-00282B	PCB—CD MAIN;G3HI-3CD;		
	AJ59-20150F	DECK-LDP;CVM55R2/EXP,-,-,-,-		
	3405-000101	SWITCH-MICRO;1.6V,1A,70gf,SPST		
	3711-000826	CONNECTOR-HEADER;BOX,2P,1R,2mm,ANGLE,SN		
	AH31-10021A	MOTOR-DC;RF-500TB,9VDC/130mA,		
	AH31-12001A	MOTOR-LOADING;FF-030PN-09210		
	AH91-60150C	**ASSY CDP DECK;CMS-D73SG6(U)/JVC,CMS-300D**		
	3409-001078	SWITCH-LEAF;16Vdc,500mA,10gf,SPST		
	AH30-00007A	PICK UP;SOH-AD3,-,-,-,100*80*45,D73SG6		
	AH81-00614A	A/S-SHAFT-PU;-,METAL,-,-,-,-,-		
	AH81-00614B	A/S-SCREW;-,METAL,AJ60-00601D,-,-,-,-		
	AH81-00614C	A/S-SCREW;-,METAL,6003-000294,-,-,-,-		
	AH81-00614D	A/S-WASHER;-,PBT,AJ60-00608A,-,-,-,-		
	AH81-00614E	A/S-GEAR(C);-,PBT,AJ66-00006A,-,-,-,-		
	AH81-00614F	A/S-GEAR(B);-,PBT,AJ66-00005A,-,-,-,-		
	AH81-00614G	A/S-GEAR(A);-,PBT,AJ66-00004A,-,-,-,-		
	AH81-00614H	A/S-MOTOR-FEED;-,-,AJ31-00601E,-,-,-,-		
	AH81-00614J	A/S-MOTOR-PCB ASSY;-,-,AJ41-00601S,-,-,-		
	AH81-00614K	A/S-CONNECTOR;-,-,AJ37-00601A,-,-,-,-		
	AH59-01348B	SPEAKER SYSTEM;PSJ530E,-,-,-,-,-,-,ELS,M		
	AH81-01427A	A/S PART-SPK SYSTEM;PSJ530,-,-,SPK SYSTE		
	AH81-01427B	A/S PART-FRONT PANEL;PSJ530,HIPS,-,FRONT		
	AH81-01427C	A/S PART-WOODEN CABINET;PSJ530,WOOD,-,WO		
	AH81-01427D	A/S PART-WOOFER UNIT;PSJ530,-,-,WOOFER U		
	AH92-02019B	**ASSY PCB-MAIN;MAX-J530,-**		
FD24	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,		
FD25	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,		
FD26	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,		
FD27	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,		
FQ28	0502-000419	TR-POWER;-,PNP,25W,TO-220F,BK,100-200		
FQ33	0502-001176	TR-POWER;KTC2026,NPN,2000mW,TO-220IS,ST		
FIC3	1201-001026	IC-POWER AMP;7265,ZIP,11P,19.6MIL,DUAL,1		
FIC2	1201-001899	IC-PREAMP;HA12237F,QFP,40P,7X7MM,-,-,PLA		
FIC1	1204-001621	IC-VOLUME/TONE CONT.;LC75341,DIP,24P,300		
FC128	2201-002128	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,15X		
FC129	2201-002128	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,15X		
FC125	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
FC119	2401-001067	C-AL;3300uF,20%,42V,GP,-,18x35.5,7.		
F1	3601-000282	FUSE;250V,4A,TIME-LAG,GLASS,5.2x20m		
F2	3601-000304	FUSE-CARTRIDGE;250V,630mA,TIME-LAG,GLASS		
FW3	3708-000412	CONNECTOR-FPC/FFC/PIC;12P,1.25MM,ANGLE,-		
FW1	3708-001195	CONNECTOR-FPC/FFC/PIC;27P,1.25MM,STRAIGH		
FW13	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92MM,STRA		
FW9	3711-001011	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH		
FW2	3711-001137	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,		
FW4	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH		
FW12	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH		
FW5	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH		
FW6	3711-003409	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,		
FJ4	3716-000209	TERMINAL-BLOCK;,-,-,60V,7A		
HJCK1	3722-000351	JACK-PHONE;11P,3.5PI,AG,BLK,-		
FJ2	3722-000377	JACK-PIN;4P/2C,3.5mm,SN,BLK,#16~22		
FL14	AH26-00227A	TRANS RF;-,-,-,-,-,-,-,105KHZ,7.6 X 7.6,-		
FL8	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,		
FL7	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,		
FL12	AH27-10001T	COIL CHOKE;875-101-105K,MAX-S530,18MH##1		
FL13	AH27-10001T	COIL CHOKE;875-101-105K,MAX-S530,18MH##1		
FL4	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
FL5	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
FL6	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
FL9	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
FW11	AH39-00018B	LEAD CONNECTOR ASSY;MAX-B420,-,-,6P,-,-,		
HCW1	AH39-00249A	LEAD CONNECTOR ASSY;MX-K5,#1007,22AWG,UL		
	AH61-00250C	BRACKET-HEAT SINK;MAX-B420,SECC 0.8T,-,-		
GND	AH61-40022A	STUD-TAP;-,T0.5,BT2,-,-,-,-		
FIC3-1	AH62-00023D	HEAT SINK-MAIN;MAX-B450,AL ,-,-,-,-,-,-		
	AH81-01110D	A/S-MAIN PCB ASS'Y;MAX-S520,-,-,-,-,-,MA		
	AH81-01110F	A/S-POWER PCB ASS'Y;MAX-S520,-,-,-,-,-,P		
FD44	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD45	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD22	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD43	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD42	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD30	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD23	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD50	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD48	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD47	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD46	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD28	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD29	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD36	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD7	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD10	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD14	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		

Location no	Code no.	Description	Specification	Remarks
FD15	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD16	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
FD35	0403-000372	DIODE-ZENER;UZ9.1BM,8.7-9.4V,500MW,DO-35		
FD13	0403-000393	DIODE-ZENER;UZP5.1B,4.8-5.4V,1000MW,DO-4		
FD6	0403-000396	DIODE-ZENER;UZP6.8B,6.4-7.2V,1000MW,DO-4		
FD8	0403-000396	DIODE-ZENER;UZP6.8B,6.4-7.2V,1000MW,DO-4		
FD9	0403-000396	DIODE-ZENER;UZP6.8B,6.4-7.2V,1000MW,DO-4		
FD5	0403-000564	DIODE-ZENER;TZP16A,15.3-17.1V,1000MW,DO-		
FD4	0403-000564	DIODE-ZENER;TZP16A,15.3-17.1V,1000MW,DO-		
FQ9	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
FQ8	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
FQ7	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
FQ6	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
MQ1	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
FQ40	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
FQ39	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
FQ29	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
FQ25	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
FQ13	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
FQ23	0501-002176	TR-SMALL SIGNAL;KTD863,NPN,1W,TO-92L,TP,		
FQ14	0501-002176	TR-SMALL SIGNAL;KTD863,NPN,1W,TO-92L,TP,		
FQ5	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
FQ30	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
FQ24	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
FQ15	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
FQ36	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
FQ34	0504-001123	TR-DIGITAL;KRC103M,NPN,400MW,22K/22K,TO-		
FQ35	0504-001123	TR-DIGITAL;KRC103M,NPN,400MW,22K/22K,TO-		
FQ3	0504-001125	TR-DIGITAL;KRC110M,NPN,400MW,4.7K,TO-92M		
FQ2	0504-001125	TR-DIGITAL;KRC110M,NPN,400MW,4.7K,TO-92M		
FQ4	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
FQ10	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
FR52	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR9	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR51	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR3	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR109	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR1	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR10	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR30	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR182	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M		
FR53	2001-000023	R-CARBON;47OHM,5%,1/4W,AA,TP,2.4X6.4MM		
FR16	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM		
FR97	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR96	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR123	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR105	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR94	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR93	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR92	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR5A	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR148	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR191	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR54	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR58	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR66	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR81	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR91A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR91B	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR43	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR44	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR4	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR2	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR49	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR73	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR74	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR75	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR76	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR111	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR151	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR180	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR189	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR190	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR72	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR68	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR80	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR84	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR85	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR86	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR87	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR112	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR146	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR45	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR46	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR47	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR48	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR185	2001-000454	R-CARBON;2.2MOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR98	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR82	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR65	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR100	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR25	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR27	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM		

Location no	Code no.	Description	Specification	Remarks
FR29	2001-000515	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR20	2001-000515	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR21	2001-000515	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR23	2001-000515	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR38	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR42	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR61	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR71	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR184	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR106	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR127	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR138	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR145	2001-000522	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR60	2001-000591	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR37	2001-000591	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR128	2001-000591	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR95	2001-000613	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR91	2001-000613	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR156	2001-000613	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR152	2001-000613	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR34	2001-000660	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR33	2001-000660	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR115	2001-000660	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR108	2001-000660	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR55	2001-000689	R-CARBON	390KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR175	2001-000702	R-CARBON	39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR90	2001-000734	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR89	2001-000734	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR62	2001-000734	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR6	2001-000734	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR118	2001-000734	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR41	2001-000780	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR63	2001-000786	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR40	2001-000786	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR39	2001-000786	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR173	2001-000786	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR31	2001-000786	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR32	2001-000786	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR8	2001-000793	R-CARBON	47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR107	2001-000857	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR104	2001-000857	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR90A	2001-000890	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR89A	2001-000890	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR83	2001-000890	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR64	2001-000890	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR68	2001-000890	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR77	2001-000890	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR99	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR78	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR69	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR101	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR102	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR103	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
FR57	2001-001070	R-CARBON(S)	120OHM,5%,1/2W,AA,TP,2.4X6.4	
HR01	2001-001077	R-CARBON(S)	150OHM,5%,1/2W,AA,TP,2.4X6.4	
HR02	2001-001077	R-CARBON(S)	150OHM,5%,1/2W,AA,TP,2.4X6.4	
FR59	2001-001096	R-CARBON(S)	2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
FR136	2001-001107	R-CARBON(S)	220ohm,5%,1/2W,AA,TP,2.4x6.4	
FR160	2001-001146	R-CARBON(S)	4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
FR155A	2001-001146	R-CARBON(S)	4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
FR132	2001-001146	R-CARBON(S)	4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
FR131	2001-001146	R-CARBON(S)	4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
FR158	2001-001153	R-CARBON(S)	47OHM,5%,1/2W,AA,TP,2.4X6.4M	
FR157	2001-001153	R-CARBON(S)	47OHM,5%,1/2W,AA,TP,2.4X6.4M	
FR142	2001-001153	R-CARBON(S)	47OHM,5%,1/2W,AA,TP,2.4X6.4M	
FR172	2001-001163	R-CARBON(S)	560OHM,5%,1/2W,AA,TP,2.4X6.4	
FR171	2001-001163	R-CARBON(S)	560OHM,5%,1/2W,AA,TP,2.4X6.4	
FR122	2003-000534	R-METAL OXIDE(S)	1Kohm,5%,1W,AA,TP,3.3x9	
FR121	2003-000534	R-METAL OXIDE(S)	1Kohm,5%,1W,AA,TP,3.3x9	
FR120	2003-000534	R-METAL OXIDE(S)	1Kohm,5%,1W,AA,TP,3.3x9	
FR119	2003-000534	R-METAL OXIDE(S)	1Kohm,5%,1W,AA,TP,3.3x9	
FR116	2003-000534	R-METAL OXIDE(S)	1Kohm,5%,1W,AA,TP,3.3x9	
FR155	2003-000603	R-METAL OXIDE(S)	270ohm,5%,1W,AA,TP,3.3x	
FR117	2003-000689	R-METAL OXIDE(S)	4.7ohm,5%,1W,AA,TP,3.3x	
FR154	2008-000003	R-FUSIBLE	0.22ohm,5%,1/2W,AA,TP,3.5x9.4m	
FC146	2201-000163	C-CERAMIC,DISC	10NF,+80-20%,50V,Y5V,TP,7	
FC15	2201-000163	C-CERAMIC,DISC	10NF,+80-20%,50V,Y5V,TP,7	
FC86	2201-000163	C-CERAMIC,DISC	10NF,+80-20%,50V,Y5V,TP,7	
FC87	2201-000163	C-CERAMIC,DISC	10NF,+80-20%,50V,Y5V,TP,7	
FC21	2201-000300	C-CERAMIC,DISC	1NF,20%,50V,Y5T,TP,5X3MM,	
FC1	2201-000368	C-CERAMIC,DISC	0.22NF,10%,50V,SL,TP,6.5X	
FC2	2201-000368	C-CERAMIC,DISC	0.22NF,10%,50V,SL,TP,6.5X	
FC26	2201-000368	C-CERAMIC,DISC	0.22NF,10%,50V,SL,TP,6.5X	
FC34	2201-000368	C-CERAMIC,DISC	0.22NF,10%,50V,SL,TP,6.5X	
FC35	2201-000368	C-CERAMIC,DISC	0.22NF,10%,50V,SL,TP,6.5X	
FC88	2201-000470	C-CERAMIC,DISC	0.33NF,10%,50V,SL,TP,6.5X	
EC7	2201-000557	C-CERAMIC,DISC	0.47NF,10%,50V,SL,TP,8X3.	
FC105	2201-000565	C-CERAMIC,DISC	47nF,+80-20%,-,-,12.5x4m	
FC7	2201-000783	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,	
FC133	2201-000783	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,	
FC132	2201-000783	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,	
EC5	2201-000783	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,	
HC02	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
HC01	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
FC82	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
HC03	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
HC04	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
ML02	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
FC80	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
CM01	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
EC10	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
EC11	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
FC79	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
FC107	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
EC6	2202-000796	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3	
FC43	2202-000806	C-CERAMIC,MLC-AXIAL	220pF,10%,50V,Y5P,TP	
FC42	2202-000806	C-CERAMIC,MLC-AXIAL	220pF,10%,50V,Y5P,TP	
FC144	2202-000806	C-CERAMIC,MLC-AXIAL	220pF,10%,50V,Y5P,TP	
EC3	2202-000806	C-CERAMIC,MLC-AXIAL	220pF,10%,50V,Y5P,TP	
EC2	2202-000806	C-CERAMIC,MLC-AXIAL	220pF,10%,50V,Y5P,TP	
EC9	2202-000817	C-CERAMIC,MLC-AXIAL	4.7nF,20%,16V,Y5R,TP	
EC8	2202-000817	C-CERAMIC,MLC-AXIAL	4.7nF,20%,16V,Y5R,TP	
FC148	2202-000820	C-CERAMIC,MLC-AXIAL	5.6nF,20%,16V,Y5R,TP	
FC33	2202-000847	C-CERAMIC,MLC-AXIAL	1,8nF,30%,50V,Y5S,TP	
FC32	2202-000847	C-CERAMIC,MLC-AXIAL	1,8nF,30%,50V,Y5S,TP	
FC29	2202-000847	C-CERAMIC,MLC-AXIAL	1,8nF,30%,50V,Y5S,TP	
FC28	2202-000847	C-CERAMIC,MLC-AXIAL	1,8nF,30%,50V,Y5S,TP	
FC98	2202-000850	C-CERAMIC,MLC-AXIAL	2.2nF,20%,16V,Y5R,-,	
FC85	2202-000850	C-CERAMIC,MLC-AXIAL	2.2nF,20%,16V,Y5R,-,	
FC55	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC64	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC66	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC74	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC76	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC111	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC112	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC23	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC46	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC54	2301-000375	C-FILM,LEAD-PEF	100nF,5%,50V,TP,11x12.5x	
FC62	2301-000385	C-FILM,LEAD-PEF	12nF,10%,50V,TP,7x12x3.5	
FC72	2301-000385	C-FILM,LEAD-PEF	12nF,10%,50V,TP,7x12x3.5	
FC40	2301-000400	C-FILM,LEAD-PEF	1nF,10%,50V,TP,5.5x12x3m	
FC38	2301-000404	C-FILM,LEAD-PEF	2.2nF,10%,50V,TP,5.5x12x	
FC39	2301-000404	C-FILM,LEAD-PEF	2.2nF,10%,50V,TP,5.5x12x	
FC56	2301-000407	C-FILM,LEAD-PEF	2.7nF,10%,50V,TP,5.5x12x	
FC47	2301-000407	C-FILM,LEAD-PEF	2.7nF,10%,50V,TP,5.5x12x	
FC41	2301-000407	C-FILM,LEAD-PEF	2.7nF,10%,50V,TP,5.5x12x	
FC18	2401-000303	C-AL	100uF,20%,25V,GP,TP,6.3x11,5	
FC20	2401-000303	C-AL	100uF,20%,25V,GP,TP,6.3x11,5	
FC125	2401-000357	C-AL	100uF,20%,50V,GP,-,8x11.5,3.5m	
FC19	2401-000438	C-AL	10UF,20%,25V,GP,-,5X11,5	
FC22	2401-000438	C-AL	10UF,20%,25V,GP,-,5X11,5	
FC83	2401-000438	C-AL	10UF,20%,25V,GP,-,5X11,5	
FC96	2401-000438	C-AL	10UF,20%,25V,GP,-,5X11,5	
FC99	2401-000438	C-AL	10UF,20%,25V,GP,-,5X11,5	
FC124	2401-000475	C-AL	10uF,20%,50V,GP,TP,5x11mm,5mm	
FC108	2401-000830	C-AL	220uF,20%,25V,GP,TP,8x11.5,5	
FC45	2401-000907	C-AL	22uF,20%,16V,GP,TP,5x11mm,5mm	
FC36	2401-000907	C-AL	22uF,20%,16V,GP,TP,5x11mm,5mm	
FC84	2401-001022	C-AL	3.3UF,20%,50V,GP,TP,5X11,5	
FC97	2401-001022	C-AL	3.3UF,20%,50V,GP,TP,5X11,5	
FC212	2401-001572	C-AL	47uF,20%,50V,GP,TP,6.3x11mm,5m	
FC211	2401-001572	C-AL	47uF,20%,50V,GP,TP,6.3x11mm,5m	
FC104	2401-001625	C-AL	6.8uF,20%,50V,GP,TP,5x11,5	
FC9	2401-001895	C-AL	100uF,20%,16V,GP,TP,6.3x11,2.5	
FC145	2401-001895	C-AL	100uF,20%,16V,GP,TP,6.3x11,2.5	
FC137	2401-001895	C-AL	100uF,20%,16V,GP,TP,6.3x11,2.5	
FC57	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC58	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC59	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC60	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC61	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC70	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC81	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC52	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC123	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC24	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC37	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC48	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC49	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC50	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
FC51	2401-001912	C-AL	1uF,20%,50V,GP,BK,5x11mm,2mm	
BE3R	2401-001919	C-AL	2.2uF,20%,50V,-,TP,4x7mm,5	
BE3L	2401-001919	C-AL	2.2uF,20%,50V,-,TP,4x7mm,5	
FC53	2401-001954	C-AL	4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC44	2401-001954	C-AL	4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC27	2401-001954	C-AL	4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC25	2401-001954	C-AL	4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC150-1	2401-001954	C-AL	4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC150	2401-001954	C-AL	4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC100	2401-001954	C-AL	4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC93	2401-001969	C-AL	470uF,20%,25V,GP,TP,10x12.5,5	
FC91	2401-001969	C-AL	470uF,20%,25V,GP,TP,10x12.5,5	
FC90	2401-001969	C-AL	470uF,20%,25V,GP,TP,10x12.5,5	
FC73	2401-001975	C-AL	47uF,20%,16V,GP,TP,5x11mm,5mm	
FC71	2401-001975	C-AL	47uF,20%,16V,GP,TP,5x11mm,5mm	

Location no	Code no.	Description	Specification	Remarks
FC69	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
FC63	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
FC149	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
FC77	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
FC75	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
FC68	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
FC65	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
MH3	2701-000111	INDUCTOR-AXIAL;100uH,10%,2534		
HL02	2701-000111	INDUCTOR-AXIAL;100uH,10%,2534		
HL01	2701-000111	INDUCTOR-AXIAL;100uH,10%,2534		
FL10	2701-000179	INDUCTOR-AXIAL;33uH,10%,4298		
FL1	2701-000298	INDUCTOR-AXIAL;470uH,10%,4298		
FL11	2701-000298	INDUCTOR-AXIAL;470uH,10%,4298		
FF2	3602-000147	FUSE-CLIP;250V,7.5A,30mohm		
FF1	3602-000147	FUSE-CLIP;250V,7.5A,30mohm		
FIC5	AC14-12001G	IC;KA78L05,T,-		
PCB	AH41-00664A	PCB;MAX-J530,####,1 LAYER,-,-,.163X		
	AH92-02020B	**ASSY PCB-FRONT;MAX-J530,-**		
IC3	0903-001273	IC-MICROCONTROLLER;LC87F67C8A,8BIT,QFP,1		
UX01	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5		
UX02	2802-001174	RESONATOR-CERAMIC;10MHZ,0.5%,BK,8X3.5X3M		
USR02	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm		
USR04	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
USR03	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UCW3	3708-000178	CONNECTOR-FPC/FFC/PIC;16P,1.25MM,ANGLE,S		
UCW2	3708-000454	CONNECTOR-FPC/FFC/PIC;22P,1.25MM,STRAIGH		
UCW1	3708-001195	CONNECTOR-FPC/FFC/PIC;27P,1.25MM,STRAIGH		
UCN1	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5MM,STRAIGH		
FLT1	AH07-00120A	VF DISPLAY;HNA-12LS06,MAX-ZJ550,90X40,1/		
UCA1	AH39-20008M	LEAD CONNECTOR ASSY;5264,5395,2P,150MM,1		
TIC1	AH59-60010E	MODULE REMOCON;KSM-913TE5,-,-,25CM,G.T:#		
FLT1	AH61-01520A	HOLDER-VFD;MAX-ZJ650,ABS ,-,-,-,BLK,-		
UD20	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD18	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD17	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD16	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD15	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD21	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD7	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD4	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD25	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD24	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD23	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD22	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD13	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD3	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD12	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD11	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD10	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD4	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD12	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD9	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD8	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD7	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD6	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD5	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD16	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD14	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UQ10	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92		
UQ8	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
UQ09	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
UQ03	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
UQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ6	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ5	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ3	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ2	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ1	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
ULED1	0601-001238	LED;ROUND,RED,3.1mm,697nm		
UR17	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR18	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR22	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR2	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR3	2001-000042	R-CARBON;1KOHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR12	2001-000119	R-CARBON;680OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR13	2001-000119	R-CARBON;680OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR9	2001-000119	R-CARBON;680OHM,5%,1/4W,AA,TP,2.4X6.4MM		
KR22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR2	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR12	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR3	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR23	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR13	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR54	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR55	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR56	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR57	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR58	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		

Location no	Code no.	Description	Specification	Remarks
UR53	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR42	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR43	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR44	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR51	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR52	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR36	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR37	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR38	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR35	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR34	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR33	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR32	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR31	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR8	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR7	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR6	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR59	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR5	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR48	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR41	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR40	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR4	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR26	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR25	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR24	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR23	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR22	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR21	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR29	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR20	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR10	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR11	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR34	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR33	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR32	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR31	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR27	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR28	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR29	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR30	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR27	2001-000295	R-CARBON;10MOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR23	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR8	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR28	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR18	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR30	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR45	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR46	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR1	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UJ41	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR21	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR11	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR1	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR29	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR14	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR25	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR4	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR26	2001-000508	R-CARBON;220KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR19	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR21	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR15	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR25	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR5	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR15	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
LR5	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR4	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR37	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR36	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR3	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR20	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR9	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR8	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR7	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR6	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR20	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR14	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR13	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR12	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR11	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR1	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR10	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR2	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR19	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR18	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR15	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR16	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
LR17	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR50	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		

Location no	Code no.	Description	Specification	Remarks
UR16	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR14	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR10	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR6	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR26	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR16	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR9	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR19	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR28	2001-000850	R-CARBON;560KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR27	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR7	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR17	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
USR1	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP		
LC4	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
LC2	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
UC2	2201-000389	C-CERAMIC,DISC;0.022NF,5%,50V,C0G,TP,5X3		
UC1	2201-000389	C-CERAMIC,DISC;0.022NF,5%,50V,C0G,TP,5X3		
UC7	2201-000564	C-CERAMIC,DISC;47NF,+80-20%,50V,Y5V,TP,6		
UC3	2201-000564	C-CERAMIC,DISC;47NF,+80-20%,50V,Y5V,TP,6		
LC3	2201-000564	C-CERAMIC,DISC;47NF,+80-20%,50V,Y5V,TP,6		
LC1	2201-000564	C-CERAMIC,DISC;47NF,+80-20%,50V,Y5V,TP,6		
UC6	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.		
UC5	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.		
UC4	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.		
UE1	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
LE1	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm		
LE2	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm		
UE4	2401-000759	C-AL;220nF,20%,50V,GP,TP,5x11mm,5mm		
UE2	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5		
UE3	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
UK27	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK28	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK29	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK26	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK25	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK24	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK23	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK22	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK15	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK14	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK21	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK20	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK19	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK18	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK17	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
UK16	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
FRONT-PCB	AH41-00653B	PCB-FRONT;MAX-J530,PENOL,1 LAYER,-,-,247		
	AH97-01099A	**ASSY-ASS'Y CA'DECK;-,MAXS520/S530,ASSY C**		
	AH39-00022A	LEAD CONNECTOR ASSY;5247#81SHI,EP,ELLDD,		
	AH39-20002D	LEAD CONNECTOR ASSY;5264,-,3P,300MM,2970		
	AH59-01144A	DECK-CASSETTE;ADR268DSW1,MAXS530,-,-,DC1		